

RE-717M

MANUAL CALL POINT

General

The RE-717M Manual Call Point is compliant with latest standards and is designed to interface with Ravel addressable fire alarm panel, Avani. DIP switches are provided for addressing of the call point. The RED blinking LED indicates normal operating condition. Activation of MCP is indicated by RED steady LED.




Features

- Complies EN54-11.
- Inbuilt isolator.
- Type "A" Indoor Use.
- Resettable by an element kit.
- Suitable for flush or surface mounting.
- Module Addressing by 8-way DIP Switches.
- Low Standby Current.

Specification

Electrical Specification	
Operating Voltage	24VDC.
Power-up surge current	0.8mA
Quiescent Current	0.5mA
Alarm Current	2.5mA
Temperature	0 – 49°C
Relative Humidity	0 - 93% non-condensing
Connection	2.5mm ² Max.
Weight	125g
IP Rating	IP 50
Dimensions	86mm X 86mm X 50 mm

Wiring Diagram



Note:-

Input & Output + / - are sensitive, be ensure that wiring before power up.

Ordering Information

Model	Description
RE-717M	Analogue Addressable Manual Call Point

India

RAVEL ELECTRONICS PVT LTD.,
150A, Electronics Industrial Estate,
Perungudi, Chennai – 96, India.
E-mail: sales@ravelfire.com; Web: www.ravelfire.com

UAE

RAVEL DMCC,
Unit No: G30, DMCC Business Center,
Level No 13, AG Tower, Dubai, UAE.
E-mail: sales@raveldmcc.com

USA

RAVEL AMERICAS INC.,
2855 NW 112th Ave ST#2 Miami,
Doral, Florida 33172, USA.
E-mail: sales.us@ravelfire.com